CROSSTECH PROFESSIONAL TORCHESTM With New Solder Clean Out Feature

MAPP® / PROPANE TORCHES WITH CROSSWIRL™ BURNERS

PROVEN DESIGN WITH OVER 21 YEARS OF FIELD USE



Users can now easily repair their torches if they accidentally melt solder into the torch tip. This is simply done by unscrewing the brass fittings and removing the solder that is easily visible. Low cost replacement flame tubes, P/N FT2000CLO, that hold the flame stabilizer can be purchased from local distributors.

PERFORMANCE

TM2000CLO:

BTU'S/HR W/MAPP®: 11,530

COPPER TUBING SIZE CAPACITY

PROPANE

SOFT SOLDER: 1 1/2" SILVER SOLDER: 3/4" COPPER-PHOS.: 1/2"

MAPP®

SOFT SOLDER: 2 1/2"
SILVER SOLDER: 1 1/2"
COPPER-PHOS.: 1"

TM2100CLO:

BTU'S/HR W/MAPP®: 21,880

COPPER TUBING SIZE CAPACITY

PROPANE

SOFT SOLDER: 2 1/2"
SILVER SOLDER: 1 1/2"
COPPER-PHOS.: 1"

 $\mathsf{IAPP}^{\mathsf{u}}$

SOFT SOLDER: 4"
SILVER SOLDER: 2 1/2"
COPPER-PHOS.: 1 3/4"
These are conservative ratings.